

GUJARAT TECHNOLOGICAL UNIVERSITY**BE - SEMESTER-VII (OLD) EXAMINATION – SUMMER 2019****Subject Code: 171003****Date: 16/05/2019****Subject Name: Digital Signal Processing****Time: 02:30 PM TO 05:00 PM****Total Marks: 70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

Q.1 (a) Draw the block diagram architecture of TMS320C6000 series Digital Signal Processor. Briefly describe each block functions. **07**

(b) Define ROC for z-transform? List the properties of the ROC. **07**

Q.2 (a) State and prove Time Shifting and Scaling in z domain properties for z-transform. **07**

(b) State and prove convolution theorem and the correlation theorem for Fourier transform **07**

OR

(b) Determine the z-transform of the following signals. **07**

i) $x(n) = u(n)$ (3-Marks)

ii) $x(n) = (\cos \omega_0 n)u(n)$ (4-Marks)

Q.3 (a) Determine the inverse z-transform of $X(z) = \frac{1}{1 - 1.5z^{-1} + 0.5z^{-2}}$ if **07**

(i) ROC: $|z| > 1$

(ii) ROC: $|z| < 0.5$

(iii) ROC: $0.5 < |z| < 1$

(b) Determine the range of value of a and b for which the linear time-invariant system with impulse response **07**

$$h(n) = \begin{cases} a^n, & n \geq 0 \\ b^n, & n \leq 0 \end{cases}$$

is stable.

OR

Q.3 (a) Determine the spectra of the signals **07**

i) $x(n) = \cos \sqrt{2}\pi n$ (3-marks)

ii) $x(n) = \cos \pi n / 3$ (4-marks)

(b) The impulse response of a linear time invariant system is **07**

$$h(n) = \left\{ \underset{\uparrow}{1}, 2, 3, 1 \right\}$$

Determine the response of the system to the input signal

$$x(n) = \left\{ \underset{\uparrow}{1}, 2, 1, -1 \right\}$$

Q.4 (a) Compute the DFT of the four-point sequence $x(n) = \{0 \ 1 \ 2 \ 3\}$ **07**

(b) Obtain direct form-I and direct form-II structures for the system **07**

$$y(n) = \frac{3}{4} y(n-1) - \frac{1}{8} y(n-2) + x(n) + \frac{1}{3} x(n-1).$$

OR

Q.4 (a) State the Sampling theorem. Consider the analog signal **07**
 $x_a(t) = 3 \cos 2000\pi t + 5 \sin 6000\pi t + 10 \cos 12000\pi t$.

- i) What is the Nyquist rate for this signal?
- ii) Assume now that we sample this signal using a sampling rate $F_s = 5000$ samples/s. What is the discrete-time signal obtained after sampling?

(b) How many numbers of additions, multiplications and memory locations will be required to realize a system $H(z)$ having M zeros and N poles in (i) Direct-form I and Direct-form-II realization?. (ii) Give direct form-I and Direct form-II structures of second order system realization. **07**

Q.5 (a) Perform the circular convolution of the following two sequences: **07**

$$x_1(n) = \left\{ \underset{\uparrow}{2}, 1, 2, 1 \right\}$$

$$x_2(n) = \left\{ \underset{\uparrow}{1}, 2, 3, 4 \right\}$$

(b) Classify the discrete time signals. Give one example of each class. **07**

OR

Q.5 (a) Differentiate IIR and FIR systems. **07**

(b) Explain the Decimation in Time FFT algorithm. **07**
