

GUJARAT TECHNOLOGICAL UNIVERSITY**BE - SEMESTER– VII (OLD) EXAMINATION – WINTER 2021****Subject Code:171003****Date:29/11/2021****Subject Name:Digital Signal Processing****Time:02:30 PM TO 05:00 PM****Total Marks: 70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.
4. Simple and non-programmable scientific calculators are allowed.

- Q.1 (a)** Attempt following questions. **06**
 1) Explain architecture for Digital Signal Processor with its key features in detail.
- (b)** Classify the following systems. **08**
 1) Static Vs Dynamic systems
 2) Recursive Vs non-recursive systems
 3) Linear Vs non linear systems
 4) Time Variant Vs Time Invariant systems
- Q.2 (a)** Determine convolution of given discrete time sequences with graphical approach. $x(n) = \{3,11,7,0,-1,4,2\}$ for $n = -3 : 3$ and $h(n) = \{2,3,0,-5,2,1\}$ for $n = -1:4$. **07**
- (b)** Determine impulse response of following LTI systems described by the following second order difference equation. **07**
 $y(n) - 3y(n-1) - 4y(n-2) = x(n) + 2x(n-1)$
- OR**
- (b)** Discuss various properties of DTFT. Also compare DTFT with DFT. Why DFT is better? **07**
- Q.3 (a)** Discuss following properties of Z-Transform in detail with proof. **07**
 1) Convolution
 2) Differentiation
 3) Time Shifting
- (b)** Describe the properties of ROC in context with Z-Transform and determine the Z-Transform of given signal. **08**
 $x(n) = u(n) - u(n-20)$
- OR**
- Q.3 (a)** What is the need of Transformation on any signal? Compare Z Transform with DFT and FFT with examples. **07**
- (b)** Determine Partial Fraction Expansion of **07**
 $X(z) = (1+z^{-1}) / (1-z^{-1}+0.5z^{-2})$
- Q.4 (a)** Compute Circular convolution of following discrete time sequences. **07**
 $x(n) = \{1,2,2\}$ and $h(n) = \{1,2,3,4\}$
- (b)** Obtain direct form I & II, cascade and parallel form structures for the given system **07**
 $y(n) = \frac{1}{2}y(n-1) + \frac{1}{4}y(n-2) + 2x(n) - x(n-1)$
- OR**
- Q.4 (a)** Justify the following statement: Multiplication of Two DFTs is circular convolution in Time Domain. Derive relevant equations. **07**
- (b)** Compute 4 point DFT of a given discrete sequence using Radix-2 DIF FFT **07**

algorithm.

$$x(n) = \{ 1,2,3,4 \}$$

- Q.5 (a)** Explain Radix 2 DIT FFT algorithm for computing 8 point DFT. Derive all necessary equations and signify importance of bit reversal table in it. **07**
- (b)** List out benefits of Digital filter over Analog filters. Discuss parameters and their importance in designing any practical frequency selective filter. **07**

OR

- Q.5 (a)** Discuss BLT with regard to IIR filter design. Why is it more efficient than Impulse Invariance approach? **07**
- (b)** How FFT is computationally more efficient than DFT? Under which set of parameters comparison between these algorithms are possible? Comment on efficiency of FFT against DFT. **07**
