

GUJARAT TECHNOLOGICAL UNIVERSITY**BE - SEMESTER-IV (NEW) EXAMINATION – WINTER 2023****Subject Code:3141708****Date:17-01-2024****Subject Name: Control Theory****Time: 10:30 AM TO 01:00 PM****Total Marks:70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.
4. Simple and non-programmable scientific calculators are allowed.

	MARKS
Q.1 (a) Explain green engineering with suitable example.	03
(b) What is transfer function? Discuss properties, advantages, and disadvantages of it.	04
(c) What is control system? What are the different types of control systems? Compare open loop and closed-loop control system.	07
Q.2 (a) Find Laplace transform of unit step and impulse signal.	03
(b) Compare Block diagram and Signal flow graph methods.	04
(c) Draw the equivalent mechanical system of the system shown in figure.1. Write the set of equilibrium equations for it and obtain electrical analogous circuits using i) F-V analogy ii) F-I analogy	07
OR	
(c) What is an analogous system? Establish force-current and force-voltage analogy.	07
Q.3 (a) Derive transfer function of field-controlled dc motor.	03
(b) Discuss standard Test signals used in control system.	04
(c) For the block diagram of figure.2, derive the open-loop and closed-loop transfer function by block diagram reduction technique.	07
OR	
Q.3 (a) Define: Frequency response, Root locus, Centroid.	03
(b) Derive the expression for peak time T_p for a second order control system subjected to a unit step input.	04
(c) Obtain the overall transfer function using Mason's gain formula for the signal flow graph shown in Figure.3.	07
Q.4 (a) Explain bounded input bounded output (BIBO) stability.	03
(b) Define: (i) State (ii) State Variable (iii) State Vector.	04
(c) Sketch the root locus and determine the value of K for marginal stability. $G(s) = K / s (s+1) (s + 3)$.	07
OR	
Q.4 (a) What is Performance index? Define various performance indices for closed loop control system.	03
(b) Derive expression of K_P , K_V , K_A for Type '0' control system.	04
(c) The characteristic equation of a system is given by $S^6+3S^5+5S^4 + 9S^3 + 8S^2 + 6S + 4 = 0$. Investigate the stability of a system by means Routh-Hurwitz criterion.	07

- Q.5** (a) Derive unit step response of a first order system. **03**
 (b) Define the following terms 1) Gain cross over frequency 2) Phase cross over frequency 3) Gain Margin 4) Phase Margin. **04**
 (c) Sketch Bode plot of a unity feedback control system having transfer function, **07**
 $G(s) = 100(s+3) / s(s+1)(s+5)$.

OR

- Q.5** (a) Discuss Nyquist stability criterion. **03**
 (b) Sketch polar plot for the system with transfer function $G(s)H(s) = 10/s(s+2)$. **04**
 (c) Describe correlation between transfer function and state-space equations with suitable example. **07**




Figure.1




Figure.2




Figure.3