

GUJARAT TECHNOLOGICAL UNIVERSITY**BE - SEMESTER-VII (OLD) EXAMINATION – WINTER 2018****Subject Code: 171003****Date: 26/11/2018****Subject Name: Digital Signal Processing****Time: 10:30 AM TO 01:00 PM****Total Marks: 70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

Q.1 (a) A discrete-time signal $x(n]$ is defined as **07**

$$x(n) = \begin{cases} 1 + \frac{n}{3} & -3 \leq n \leq 1 \\ 1 & 0 \leq n \leq 3 \\ 0 & \text{elsewhere} \end{cases}$$

- a) Determine its value and Sketch the signal.
- b) Sketch the signal if
 - I. First fold $x(n]$ and then delay the resulting signal by four samples
 - II. First delay $x(n]$ by four samples and then fold the resulting signal
- c) Compare above results. Is folding and Delay Operation is commutative operation?
- d) Can you express the signal $x(n]$ in terms of $\delta(n]$ and $u(n]$?

(b) For each of following system determine whether system is stable, causal, Linear, Time invariant or not. **07**

1. $y(n) = \sum_{k=-\infty}^{n+1} x(k)$
2. $y(n) = x(n^2)$
3. $y(n) = \log x(n)$

Q.2 (a) Prove that convergence of absolute sum of the impulse response is a sufficient condition for BIBO (bounded input bounded output) stability of LTI system. **07****(b)** Obtain a linear convolution of following two discrete-time signals: **07**

$$x(n) = \sum_{k=0}^2 \delta(n - k)$$

$$h(n) = 2^n [u(n) - u(n - 3)]$$

OR**(b)** Enlist Properties of linear convolution. **07**Obtain linear Convolution for $x(n) = \{1, 1, 0, 1, 1\}$ and $h(n) = \{1, -2, -3, 4\}$ **Q.3 (a)** What is ROC? Explain the properties of ROC in Z-Transform. **07****(b)** Find magnitude Response and Phase Response of system described by differential equation **07**

$$y(n) - \frac{1}{2}y(n - 1) = x(n) - \frac{1}{4}x(n - 1)$$

OR

- Q.3 (a)** What is canonic and non-canonic structure? Obtain Direct form-I and Direct form II realization of the following transfer function. **07**

$$H(z) = \frac{3 + 3.6z^{-1} + 0.6z^{-2}}{1 + 0.1z^{-1} - 0.2z^{-2}}$$

- (b)** Prove differentiation property of Z-transform and obtain the Z-transform of $nu(n)$ using the same. **07**

- Q.4 (a)** The system function of the analog filter is given as **07**

$$H_a = \frac{s + 0.1}{(s + 0.1)^2 + 9}$$

Obtain the system function of the IIR digital filter by using impulse invariance method.

- (b)** State and Prove following Properties in terms of DFT. **07**

1. Time Reversal
2. Periodicity

OR

- Q.4 (a)** Compare FIR and IIR filters. **07**

- (b)** Determine the response of FIR filter using DFT if **07**

$$x(n) = \{1,2\} \text{ and } h(n) = \{2,2\}$$

\uparrow \uparrow

- Q.5 (a)** Explain Decimation in Time FFT algorithm. **07**

- (b)** Derive the DFT of the sample data sequence $x(n) = \{1,1,2,2,3,3\}$ determine the corresponding amplitude and phase spectrum. **07**

OR

- Q.5 (a)** Explain multiplier-Accumulator (MAC) hardware in DSP processors. **07**

- (b)** Discuss the applications of digital signal processing with suitable examples. **07**
