

GUJARAT TECHNOLOGICAL UNIVERSITY

BE - SEMESTER-IV(NEW) – EXAMINATION – SUMMER 2019

Subject Code:2141708

Date:13/05/2019

Subject Name: Control System

Time:02:30 PM TO 05:00 PM

Total Marks: 70

Instructions:

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

		MARKS
Q.1	(a) Differentiate between open loop system and closed loop systems.	03
	(b) Define transfer function. Find the impulse response of a system whose transfer function is $G=1/(S+6)$	04
	(c) Using block diagram reduction technique, find out overall transfer function $C(s)/R(s)$ for the diagram shown in fig.1.	07




Fig. 1

Q.2	(a) Write Meason’s gain formula and define each term of the formula.	03
	(b) Differentiate between signal flow graph and block diagram representation of system.	04
	(c) The open loop transfer function of a unity feedback system is	07

$$G(s)H(s) = \frac{k(s + 13)}{s(s + 3)(s + 7)}$$

Using Routh’s criterion, calculate the range of k for system to be stable. If the value of $k=1$, comment on stability.

OR

Q.3	(c) Derive and draw the unit step response of second order underdamped system.	07
	(a) Define the following terms: (1) Type of a system (2) BIBO stability (3) Time constant	03
	(b) Briefly explain the first order system and its response to unit step input.	04
	(c) Sketch the root locus plot of a control system whose open loop transfer function is given by	07

$$G(s)H(s) = \frac{k}{s(s + 4)(s^2 + 4s + 8)}$$

OR

Q.3	(a) Explain the concept of linearity and time invariance in the context of control system.	03
	(b) Define following terms: (1) rise time (2) peak time (3) settling time (4) peak overshoot	04

- (c) Draw the root locus plot of a control system whose open loop transfer function is given by **07**

$$G(s)H(s) = \frac{k}{s(s+1)(s+5)}$$

- Q.4** (a) Determine the transfer function of a system described by following state space model **03**

$$A = \begin{bmatrix} -2 & 1 \\ 0 & -1 \end{bmatrix}, \quad B = \begin{bmatrix} 1 \\ 1 \end{bmatrix}, \quad C = [1 \quad 1], \quad D=0$$

- (b) State the properties of state transition matrix. **04**
 (c) Consider an open loop transfer function **07**

$$G(s)H(s) = \frac{50}{(s+1)(s+2)}$$

Using Nyquist stability criterion, determine whether the system is stable when the feedback path is closed.

OR

- Q.4** (a) Discuss the limitations of transfer functions and advantages of analysis of control systems using state space. **03**
 (b) Write a note on steady state error and error constants. **04**
 (c) Explain Nyquist stability criterion. **07**

- Q.5** (a) Define bandwidth, gain margin and phase margin for frequency response. **03**
 (b) Draw the polar plot of $G(s) = 10/[s(s+2)]$. **04**
 (c) The open loop transfer function of a unity feedback system is **07**

$$G(s)H(s) = \frac{50}{s(s+10)(s+5)(s+1)}$$

From the Bode plot, determine gain margin and phase margin.

OR

- Q.5** (a) Discuss the effect of time delay on the stability of the process. **03**
 (b) Discuss Nichol's chart and its application. **04**
 (c) The open loop transfer function of a unity feedback system is given by **07**

$$G(s)H(s) = \frac{10(1+0.5s)}{s(0.1s+1)(0.2s+1)}$$

Draw the Bode plot and determine gain margin and phase margin.
